



LUNaPhone SIP ATA Configuration Manual

In your Cisco ATA configuration page fill the following fields:

- UID0 and UID1 should be filled with different values: for example UID0: 100 and UID1: 101
- GKorProxy: 216.206.188.214.5070
- UseLoginID: 1
- LoginID0 and LoginID1: LUNaPhone PIN
- PWD0 and PWD1: LUNaPhone Password
- SIPRegOn: 0
- OutBoundProxy : 216.206.188.214.5070
- NatServer : 216.206.188.198.3478
- NatTimer: 0x0005000f

Please look at the example – the fields you should change are marked with red

StaticRoute:	1.0.0.0	StaticNetMask:	255.255.255.0
UID0:	100	PWD0:	*****
UID1:	101	PWD1:	*****
GKorProxy:	216.206.188.214.5070	UseLoginID:	1
LoginID0:	ata2005	LoginID1:	ata2005
AltGk:	0	AltGkTimeOut:	0
SIPRegInterval:	3600	MaxRedirect:	5
SIPRegOn:	0	NATIP:	0.0.0.0
SIPPort:	5060	MediaPort:	16386
OutBoundProxy:	216.206.188.214.5070	NatServer:	216.206.188.198.3478
NatTimer:	0x0005000f	MsgRetryLimits:	0x00000000
SessionTimer:	0x00000000	SessionInterval:	1800
MinSessionInterval:	1800	DisplayName0:	0
DisplayName1:	0	LBRCodec:	3
AudioMode:	0x00150015	RxCCodec:	3
TxCodec:	3	NumTxFrames:	2
CallFeatures:	0xffffffff	PaidFeatures:	0xffffffff
CallerIdMethod:	0x00019e60	FeatureTimer:	0x00000000
FeatureTimer2:	0x0000001e	Polarity:	0x00000000
ConnectMode:	0x00060400	TimeZone:	4
NTPIP:	0.0.0.0	AltNTPIP:	0.0.0.0
DNS1IP:	202.131.99.43	DNS2IP:	0.0.0.0
...